

UNIVERSIDADE DE SÃO PAULO

# PUBLICAÇÕES

INSTITUTO DE FÍSICA  
CAIXA POSTAL 66318  
05389-970 SÃO PAULO - SP  
BRASIL

IFUSP/P-1181

DELAY-INDUCED TRANSIENT OSCILLATIONS IN A  
TWO-NEURON NETWORK

K. Pakdaman<sup>1</sup>, C. Grotta-Ragazzo<sup>2</sup>, C.P. Malta<sup>3</sup> and  
J.-F. Vibert<sup>1</sup>

1) B3E, INSERM U 263, ISARS  
Falcuté de Médecine Saint-Antoine  
27, rue Chaligny, 75571 Paris Cedex 12, France

2) Instituto de Matemática e Estatística  
Universidade de São Paulo  
CP 66281, 05389-970, São Paulo, BRASIL

3) Instituto de Física, Universidade de São Paulo

Novembro/1995

K. Pakdaman<sup>1</sup>, C. Grotta-Ragazzo<sup>2</sup>, C.P. Malta<sup>3</sup> and J.-F. Vibert<sup>1</sup>

1) B3E, INSERM U 263, ISARS, Faculté de Médecine Saint-Antoine  
27, rue Chaligny, 75571 Paris Cedex 12 FRANCE

2) Instituto de Matemática e Estatística, Universidade de São Paulo  
CP 66281, 05389-970 São Paulo, BRASIL  
Mathematics Department, Princeton University  
Fine Hall, Washington Road  
Princeton, NJ 18540 USA

3) Instituto de Física, Universidade de São Paulo  
CP 66318, 05389-970 São Paulo, BRASIL

Correspondence should be addressed to:

K. Pakdaman  
B3E, INSERM U263  
Faculté de Médecine Saint-Antoine  
27, rue Chaligny  
75571 Paris Cedex 12, FRANCE  
tel: 33-1-44738430  
fax: 33-1-44738462  
email: pakdaman@b3e.jussieu.fr

**Abstract:** Finite transmission times between neurons, referred to as delays, may appear in hardware implementation of neural networks. We analyse the dynamics of a two-neuron network in which the delay modifies the transient and not the long-term behavior of the network. We show that the delay causes some trajectories to oscillate transiently before reaching stationary behavior and the duration of these transients increases exponentially with the delay. Such a phenomenon deteriorates network performance.

**Keywords:**

Continuous time neural network  
Nonlinear graded response neuron  
Transient regime  
Delay  
Oscillation

**Acknowledgment:** The authors would like to thank Pr. O. Arino for helpful discussions. This work was partially supported by COFECUB under project U/C 9/94. One of us (CPM) is also partially supported by CNPq (the Brazilian Research Council).

**Abstract:** Finite transmission times between neurons, referred to as delays, may appear in hardware implementation of neural networks. We analyze the dynamics of a two-neuron network in which the delay modifies the transient and not the long-term behavior of the network. We show that the delay causes some trajectories to oscillate transiently before reaching stationary behavior and the duration of these transients increases exponentially with the delay. Such a phenomenon deteriorates network performance.

## 1 Introduction

In many neural network applications, "information" is stored as stable equilibria of a convergent or almost convergent system [1,2]. Thus, a given information is retrieved by initializing the network at a point within the attraction of the corresponding equilibrium point and letting the system reach its steady state.

Finite inter-unit transmission times, referred to as delays, present in hardware implementation of neural networks can interfere with information retrieval in three ways. *i)* Delays may cause a stable equilibrium point to become unstable, thus rendering the retrieval of the stored information impossible. *ii)* The network with delay may exhibit attractors that are not present in the system without delay [3,4]. For initial conditions (ICs) within the attraction of these attractors, the network activity displays sustained oscillations and no information is retrieved. *iii)* The classification of the stable equilibria and, consequently, the classification of ICs performed by the network, is altered by the delay [5].

These can be avoided if the following three respective properties hold: (P1) *local stability of all stable equilibria is preserved in presence of delays* [6-8], (P2) *the network with delay is convergent or almost convergent* [6,7], (P3) *for constant initial functions, the basins of attractions of stable equilibria are independent of the delay*.

The dynamics of a two-neuron network satisfying (P1), (P2) and (P3), is studied. It is shown that even when the steady state is unaffected by the delay, information retrieval may deteriorate due to considerable lengthening of the transient regime duration.

## 2 The model

The dynamics of two identical nonlinear graded response neurons (NGRNs) [1] connected to each other by symmetric positive weights  $W > 0$  and delays  $A > 0$ , are determined by the following delayed differential equations

$$\begin{cases} \frac{dx}{dt}(t) = -x(t) + W\sigma_\alpha(y(t-A)) \\ \frac{dy}{dt}(t) = -y(t) + W\sigma_\alpha(x(t-A)) \end{cases}$$

$$\text{where } \sigma_\alpha(x) = \tanh(\alpha x) = \frac{e^{\alpha x} - e^{-\alpha x}}{e^{\alpha x} + e^{-\alpha x}} \text{ for } 0 < \alpha < \infty \text{ and } \sigma_\infty(x) = \begin{cases} 1 & \text{for } x > 0 \\ -1 & \text{for } x \leq 0 \end{cases} \text{ for } \alpha = \infty$$

For  $\alpha = \infty$ , there are two locally asymptotically stable equilibria,  $r_1 = (-W, -W)$  and  $r_3 = (W, W)$  (Fig. 1). The basins of attraction of  $r_1$  and  $r_3$  for constant initial conditions are  $\{(u, v) \in \mathbb{R}^2, u < -v\} \cup \{(0, 0), (u, v), u > -v\}$  respectively. Thus, (P1) and (P2) are satisfied, and (P3) holds for  $r_3$ .

For  $0 < \alpha < \infty$ , the positive feedback condition ( $W > 0$ ) [5,13,14] and the invariance of (1) under the transformations  $x \rightarrow -x, y \rightarrow -y$  and  $x \rightarrow y, y \rightarrow x$ , imply the following. For  $0 < \alpha W < 1$ ,  $r_0 = (0, 0)$  is a globally asymptotically stable equilibrium point. For  $1 < \alpha W < \infty$ , there are one unstable ( $r_2 = (0, 0)$ ) and two locally asymptotically stable ( $r_1 = (-a, -a)$ ,  $r_3 = (a, a)$ ) equilibrium points ( $a$  is the strictly positive solution of  $-x + W \tanh(\alpha x) = 0$ ). The basins of attraction of  $r_1$  and  $r_3$  for constant initial conditions are  $\{(u, v), u < -v\}$  and  $\{(u, v), u > -v\}$  respectively. Thus, for  $0 < \alpha < \infty$ , (P1), (P2) and (P3) are satisfied.

### 3 Transient regime

In this section, the transient regime for the ICs  $r = (u, v)$  with  $v > -u \geq 0$  is studied. The transient regime refers to the dynamics before the system stabilizes to its steady state. Practically, the transient regime ends when the state of the system cannot be distinguished from the equilibrium point with some given precision  $\eta$ . We denote by  $T(r, A)$  the transient regime duration (TRD) of a solution  $z(t, r) = (x(t, r), y(t, r))$  of (1) with IC  $r$ .  $z(t, r) = (x(t, r), y(t, r))$  has a zero at time  $t$  if  $x(t, r) \times y(t, r) = 0$ , and we denote by  $N(r, A)$  the number of zeros of  $z(t, r)$ .

Case of  $\alpha = \infty$ . For  $\alpha = \infty$ , solutions are characterized by iterates of a one-dimensional map (appendix A), which yields the following result.

There is a sequence  $v_1(A) > v_2(A) > \dots > v_k(A) > \dots > 0$ , tending to zero as  $k \rightarrow \infty$ , such that for an integer  $p$ :

$$N(r, A) = \begin{cases} 1 & v > v_1 - (1 + \frac{v}{W})u \\ 2p \ (p \geq 1) & \text{and } T(r, A) \geq pA \text{ for } v = v_p - (1 + \frac{v}{W})u \\ 2p + 1 \ (p \geq 1) & v_{p+1} - (1 + \frac{v_{p+1}}{W})u < v < v_p - (1 + \frac{v}{W})u \end{cases}$$

FIGURE 1 HERE

The temporal evolutions and trajectory of a solution with 29 zeros are represented in Figs. 1-A and 1-C, showing the oscillatory transient prior to stabilization at  $r_3$ . In Fig. 1-B, dotted lines correspond to ICs  $r$  with even  $N(r, A)$  indicated on the line, and regions between two consecutive lines correspond to ICs  $r$  with the odd  $N(r, A)$  indicated. From the description of the trajectories it can be derived that the TRD increases with the number of zeros. This is illustrated in Fig. 1-D showing the TRD for ICs  $(-10^{-3}, v)$ . Each "hump" (for  $A = 2$  and  $A = 3$ ) corresponds to ICs that have the same number of zeros. For example, the humps indicated by stars correspond to the TRD of solutions with three zeros.

Furthermore, for a fixed IC  $r = (u, v)$  ( $v > -u \geq 0$ ), there is an unbounded sequence of delays  $0 < A_1 < A_2 < \dots < A_k < \dots$ , such that  $z(t, r)$  has exactly  $1, 2p$  or  $2p + 1$  zero(s) for  $A < A_1$ ,  $A = A_p$  or  $A_p < A < A_{p+1}$ , respectively. Thus, for large enough delays,  $N(r, A)$ , and consequently  $T(r, A)$  are increasing functions of  $A$ . The expression of  $v_n(A)$  (appendix A), indicates that the rate of increase is exponential. This is in accord with numerical results as exemplified by the dotted line in Fig. 1-F.

Case of  $1 < \alpha W < \infty$ . For ICs  $r = (u, v)$  with  $u = -v$  on the boundary, the solutions satisfy a scalar delay differential equation with negative feedback:

$$\begin{cases} \frac{dx}{dt}(t) = -x(t) - W \tanh(\alpha x(t - A)) \\ y(t) = -x(t) \end{cases} \quad (2)$$

Thus, for large enough delays ( $A > \frac{1}{\sqrt{\alpha^2 W^2 - 1} \arccos(\frac{1}{\alpha W})}$ ) solutions of constant initial conditions  $r = (u, v)$  with  $u = -v \neq 0$ , tend to periodic oscillations [15]. The continuous dependence of solutions on ICs for finite  $\alpha$  implies that, for large enough delays, solutions of (1) close to the boundary, display transient oscillations before converging. The closer the IC is to the boundary, the longer the duration of the transient oscillations. Figure 1-E represents the TRD for  $\alpha = 2.5$  and for three delay values ( $A = 0.1, 2$  and  $3$ ), for ICs  $(-10^{-3}, v)$ , with  $v$  ranging from  $10^{-3}$  to 100. Solutions displaying transient oscillations correspond to ICs to the left of the sudden change of slope in the curves (around  $v = 3$  for  $A = 2$  and  $v = 12$  for  $A = 3$ , indicated by arrows).

Figure 1-F shows the TRD for a given IC  $(u, v) = (-10^{-3}, 5)$  as function of the delay  $A$ , for three values of  $\alpha$  (0.5, 1 and  $\infty$ ). As the delay increases, the TRD undergoes an exponential increase in all three curves. For larger  $\alpha$ , the increase in the TRD is faster. However, for a given  $\alpha$ , the rapid increase in the TRD does not take place at the same delay value for all ICs.

In summary. For  $1/W < \alpha \leq \infty$ , we have shown that: i) For a fixed delay, there are ICs in the neighborhood of the boundary that display delay-induced oscillatory transients, the size of this neighborhood increases with the delay so that ii) for any IC  $(u, v)$  such that  $v > -u > 0$  the TRD increases exponentially with the delay, due to the onset of transient oscillations.

### 4 Discussion and conclusion

We showed that due to the onset of delay-induced transient oscillations, the TRD of some ICs underwe increase with the delay, even though the presence of delay did not alter the asymptotic behavior of the sy

An important issue is to determine whether a given network architecture, is prone to delay-induced t oscillations similar to those described in this paper. The lengthening of the TRD which results from the oscillations can be detrimental to the network performance. This preliminary investigation suggests tha induced transient oscillations can be related to the behavior of the discrete-time system obtained at the limit  $A \rightarrow \infty$ . For Eq. (1) the discrete time system is given by:

$$\begin{cases} x(t+1) = W\sigma_\alpha(y(t)) \\ y(t+1) = W\sigma_\alpha(x(t)) \end{cases}$$

System (3) has the same stable and unstable equilibria as Eq. (1). However, the former has also a stable pe cycle formed by the succession of  $(a, -a)$  and  $(-a, a)$ , which attracts trajectories of ICs  $(u, v)$  with  $u, v <$

The transient oscillations observed in the continuous time system reflect this change of behavior at the limit. Therefore, stable limit cycles in the discrete-time system associated with an almost convergent system, indicates delay-induced transient oscillations and the respective ICs.

### 5 Reference

- [1] J.J. Hopfield. Neurons with graded response have collective computational properties like those two-state neurons, *Proceedings National Academy of Science USA* vol. 81, pp. 3088-3092, 1984.
- [2] M.W. Hirsch. Convergent activation dynamics in continuous time networks, *Neural Networks* vol. pp. 331, 1989.
- [3] C.M. Marcus, F.R. Waugh and R.M. Westervelt. Nonlinear dynamics and stability of analog neu networks. *Physica D* vol. 51, pp. 234-247, 1991.
- [4] J. Bélair. Stability in a model of a delayed neural network, *Journal of Dynamics and Different Equations* vol. 5, pp. 607-623, 1993.
- [5] H. Ye, A.N. Michel and K. Wang. Global stability and local stability of Hopfield neural networks wi delays, *Physical Review E* vol. 50, pp. 4206-4213, 1994.
- [6] M. Gilli. Strange attractors in delayed cellular neural networks, *IEEE Transactions on Circuits a Systems-I: Fundamental Theory and Applications* vol. 40, pp. 849-853, 1993.
- [7] C.M. Marcus and R.M. Westervelt. Stability of analog neural networks with delay, *Physical Review* vol. 39, pp. 347-359, 1989.
- [8] T.A. Burton. Averaged neural networks, *Neural Networks* vol. 6, pp. 677-680, 1993.
- [9] P.P. Civalleri, M. Gilli and L. Pandolfi. On stability of cellular neural networks with delay, *IEE Transactions on Circuits and Systems-I: Fundamental Theory and Applications* vol. 40, pp. 157-161 1993.
- [10] K. Gopalsamy and X.-Z. He. Stability in asymmetric Hopfield nets with transmission delays, *Physi D* vol. 76, pp. 344-358, 1994.
- [11] T. Roska, C.F. Wu and L.O. Chua. Stability of cellular neural networks with dominant nonlinear and delay-type templates, *IEEE Transactions on Circuits and Systems-I: Fundamental Theory a Applications* vol. 40, pp. 270-272, 1993.
- [12] T. Roska, C.F. Wu, M. Balse and L.O. Chua. Stability and dynamics of delay-type general and cellu neural networks, *IEEE Transactions on Circuits and Systems-I: Fundamental Theory and Applicatio* vol. 39, pp. 487-490, 1992.

# FIGURE LEGENDS

and

# FIGURES

- [13] K. Pakdaman, C. Grotta-Ragazzo, C.P. Malta, and J.-F. Vibert. Effect of delay on the boundary of the basin of attraction in a system of two neurons, *Technical report IFUSP/P-1169, Instituto de Física, Universidade de São Paulo, Brasil*, 1995.
- [14] H. Smith. Monotone semiflows generated by functional differential equations, *Journal of Differential Equations* vol. 66, pp. 420-442, 1987.
- [15] H.-O. Walther. The 2-dimensional attractor of  $x'(t) = -\mu x(t) + f(x(t-1))$ , *Memoirs of the American Mathematical Society* vol. 113, n 544, 1995.

## A Analysis for $\alpha = \infty$

For  $r = (u, v) \in \mathbb{R}^2$ , such that  $v > -u \geq 0$ , let  $V(r) = W(v+u)/(W-u)$  and  $n$  the integer such that  $f^{n-1}(V(r)) < v_1 \leq f^n(V(r))$ , where  $v_1 = W(e^A - 1)$ ,  $f(v) = \frac{W(2+e^{-A})v}{2W \pm (v+W)e^{-A}}$  and  $f^n$  represents  $f$  iterated  $n$  times. Then, there is  $T \geq nA$ , and  $\theta > 0$  such that for  $t \geq T$   $z(t, r) = z(t - \theta, r_n)$ , where  $z(t, r)$  is the solution of (1) for the IC  $r$ , and  $r_n$  represents  $(0, f^n(V(r)))$ , for  $n$  even, and  $(f^n(V(r)), 0)$  for  $n$  odd. An example of a trajectory with  $n = 3$  is shown in Fig. 1-G.

Thus, the sequence  $v_n$  is defined by:  $v_n = f^{-n}(v_1) = \frac{2W(2-e^{-A})^n(e^A-1)}{2(2+e^{-A})^n(2+e^{-A})^n - (2-e^{-A})^n(e^A-1)}$ .  $v_n \sim \frac{2We^A}{n+2}$  as  $A \rightarrow \infty$ .

Figure 1

Figure 1: Transient regime for constant initial conditions.  
 A: Temporal evolution of  $x(t)$  (thick line) and  $y(t)$  (thin line) for  $\alpha = \infty$  and delay  $A = 3$ ,  $IC(u, v) = (-10^{-3}, 5)$ . Abscissa: activation in a.u.; ordinate: time in same a.u. as delay.  
 B: Regions in the  $(u, v)$ -plane corresponding to different transients for  $\alpha = \infty$ . The line  $v = -u$  is the boundary separating the basins of the two equilibria,  $r_1$  and  $r_3$ . For  $v > -u \geq 0$ , solutions of ICs within a given area delimited by two consecutive dashed lines have the odd number of zeros indicated. Even numbers correspond to the number of zeros of solutions with ICs on the dashed lines.  
 C: Trajectory in  $(x, y)$ -plane of same IC  $(u, v)$  as in A. Abscissa and ordinate: activation in a.u..  
 D-E: TRD with precision  $\eta = 10^{-2}$ , for delays equal to  $A = 0.1$  (solid line),  $A = 2$  (dashed line) and  $A = 3$  (dotted line) for ICs  $(u, v)$ , with  $u = -10^{-3}$ , and  $v$  ranging from  $10^{-3}$  to 100, for  $\alpha = \infty$  (D) and  $\alpha = 2.5$  (E). Abscissa:  $v$  in a.u.; ordinate: TRD in a.u..  
 F: Transient regime duration (TRD) with precision  $\eta = 10^{-3}$ , for a given IC  $(u, v) = (-10^{-3}, 5)$  as a function of the delay for three different gains  $\alpha = 0.5$  (solid line),  $\alpha = 1$  (dashed line) and  $\alpha = \infty$  (dotted line). Abscissa: delay in arbitrary units (a.u.) and ordinate: TRD same units as delay.  
 G: Trajectory of  $r = (0, v)$  in the  $(x, y)$ -plane. For all figures:  $W = 3$ .

